



The new iGen7500S delivers high-capacity portable power for home backup, food vans and recreational use. Its powerful performance, extended run time and three 240-Volt AC 15-Amp outlets provide convenient power for multiple appliances and tools at the same time. Combining reliable inverter technology with everyday practicality, the iGen7500S is a versatile solution for a wide range of portable power applications.

iGen7500s Inverter Generator

6000	7500
Running Watts	Starting Watts

Features and Benefits



Powerful

Highest starting and running power outputs in its class.

Remote Control

Convenient push-button start and stop from a distance.

Battery Charger

Keep your generator ready to go at all times.

Super Quiet

Low noise level ideal for workplace use.

Portable

Ergonomic lifting handles and Never-Flat wheels.

Plug and Play

No assembly required, just add petrol.

Electric Start

One touch power-up from the onboard 12-Volt battery.

LED Lights

Illuminate control panel for night-time operation.

15-Amp Socket Outlets

3 outlet individually switched powerboard.

Long Running

Up to 14.6 hours at 1/4 load with a 15 litre fuel tank.

Mains Quality Electricity

Safe to power sensitive electronic equipment.

Warranty Protection

2-year domestic use (conditions apply).



Run Time to Empty (hours)	Output Power (kW)	Fuel Level (litres)	Output Voltage (Volts)	Cumulative Run Time (hours)
10:29	P2.88	06.0L	U240	0168

Data Center

Indicator and Warning Lights

Fuel Switch

LED Panel Lights

Battery Charging Inlet

Panel Lights Switch

240-Volt AC Switch



240-Volt AC Switches

Engine Switch

Battery Switch

ECO Throttle Switch

Reset Button

LED Panel Lights

Frame Terminal

240-Volt AC 15-Amp Outlets

Specifications

iGen7500s

Inverter Generator

ENGINE		240 VOLT AC ELECTRICAL	
Type	1-Cylinder, 4-Stroke, Overhead Valve, Air Cooled	Voltage (V)	240
Displacement (cc)	298	Frequency (Hz)	50
Maximum Speed (rpm)	4,000	Number of Phases	1
Oil Capacity (mL)	650	Continuous Running Power (W) *	6,000
Oil Viscosity	SAE 10W-30	Maximum Starting Power (W)	7,500
Low Oil Shutdown	Yes	Continuous Running Current (A)	25
Low Oil Alarm Indicator	Yes	Voltage & Waveform Control	Digital Inverter, Pure Sine Wave Output
Spark Plug	Torch F7RTC	Total Harmonic Distortion (THD)	< 2.5%
Fuel	Unleaded Petrol # (91, 95 or 98 RON)	Receptacles	3 x 15 A, IP44
Fuel Tank Capacity (L)	15	Overload Protection	Electronic
Fuel Shutoff Valve	Yes, Independent	Overload Indicator	Yes
Starting Method	Local / Remote Electric and Recoil	Overload Reset	Push Button
Battery	12 V, Maintenance Free	Alternator	Brushless, Permanent Magnet
Run Time @ 1/4 / Full Load	14.6 / 4.6 hours	Output Ready Indicator	Yes
Noise Level @ 1/4 / Full Load	57 / 67 dB(A) @ 7 m	Data Center Display	Output Power & Voltage, Fuel Level, Fuel & Cumulative Run Times
DIMENSIONS & WEIGHTS		Control Panel Lights	LED, Operable At All Times
Generator L x W x H (mm)	690 x 530 x 550	PRODUCT CODES	
Generator Weight - Dry / Wet (kg)	60 / 73	Product Code	WP iGen7500S
Packed L x W x H (mm)	857 x 580 x 593	GTIN Barcode	9347923003512
Packed Weight (kg)	70	* Rated output at 1.0 power factor. # Ethanol blends such as E10 are not recommended.	



Plug-In Battery Charger



Extendable Handle



Included Accessories