



The new iGen1250 is the lightest and most compact Westinghouse inverter generator, yet it delivers a class-leading maximum power output of 1,250 Watts. It is an ideal portable power supply for your next camping getaway or for use as a reliable home backup to keep the lights on, fridge running and your phone charged during a blackout. The iGen1250 has all the essential connectivity, safety and operating features that you really need in an easily portable unit.

iGen1250 Inverter Generator

1000	1250
Running Watts	Starting Watts

Features and Benefits

Powerful

Highest starting and running power outputs in its class.

Super Quiet

Low dB noise level ideal for tranquil camping use.

Long Running

Up to 9.1 hours @ 1/4 load on a single tank of fuel.

Mains Quality Electricity

Safe to power all your electronic equipment.

Plug and Play

No assembly required before use, just add petrol.

Lightweight

Easy to carry 12.5 kg with its ergonomic handle.

Clean and Efficient

56 cc, 4-stroke OHV petrol engine with ECO throttle.

LED Lights

Illuminate control panel for operating at night-time.

Easy to Maintain

Engine oil and air filter servicing without tools.

Warranty Protection

2-year domestic use (conditions apply).



Control Panel Functions

Output Voltage (Volts)	Output Frequency (Hz)	Cumulative Run Time (hours)	Current Run Time (hh:mm)
U240	F50.0	0088	0 1:68



Powering People Since 1886.

Specifications

iGen1250 Inverter Generator

ENGINE		240 VOLT AC ELECTRICAL	
Type	1-Cylinder, 4-Stroke, Overhead Valve, Air Cooled	Voltage (V)	240
Displacement (cc)	56	Frequency (Hz)	50
Maximum Speed (rpm)	5,000	Number of Phases	1
Oil Capacity (mL)	250	Continuous Running Power (W) *	1,000
Oil Viscosity	SAE 10W-30	Maximum Starting Power (W)	1,250
Low Oil Shutdown	Yes	Continuous Running Current (A)	4.2
Low Oil Alarm Indicator	Yes	Voltage & Waveform Control	Digital Inverter, Pure Sine Wave Output
Spark Plug	Torch A5RTC	Total Harmonic Distortion (THD)	< 2.5%
Fuel	Unleaded Petrol # (91, 95 or 98 RON)	Receptacle	15 A, IP44
Fuel Tank Capacity (L)	3.0	Overload Protection	Electronic
Fuel Gauge	No	Overload Indicator	Yes
Fuel Shutoff Valve	Yes	Overload Reset	Push Button
Starting Method	Recoil	Alternator	Brushless, Permanent Magnet
Run Time @ 1/4 / Full Load	9.1 / 3.8 hours	Output Ready Indicator	Yes
Noise Level @ 1/4 / Full Load	54 / 61 dB(A) @ 7 m	Data Center Display	Output Voltage & Frequency, Current & Cumulative Run Times
DIMENSIONS, WEIGHTS & PRODUCT CODES		Control Panel Lights	LED, Operable While Running
Generator L x W x H (mm)	431 x 274 x 409	12 VOLT DC ELECTRICAL	
Generator Weight - Dry / Wet (kg)	12.5 / 15	Voltage (V)	12
Packed L x W x H (mm)	481 x 324 x 462	Maximum Current (A)	5
Packed Weight (kg)	15	Maximum Power (W)	60
Product Code	WP iGen1250	Receptacle	5 A, IP44
GTIN Barcode	9347923002348	* Rated output at 1.0 power factor. # Ethanol blends such as E10 are not recommended.	

