

# Westinghouse

The new iGen7500AS delivers high-capacity portable power with the flexibility of 2-wire automatic remote start for integration with off-grid solar and backup power systems. Its strong output capability, extended run time and dual outlet configuration make it suitable for larger loads such as food vans and residential backup. Combining performance, convenience and intelligent 2-wire control functionality, the iGen7500AS is a versatile solution for high-demand applications.

## iGen7500AS Inverter Generator

**6000** | **7500**  
Running Watts | Starting Watts



### Features and Benefits

#### Powerful

Highest starting and running power outputs in its class.

#### Remote Control

Convenient push-button start and stop from a distance.

#### LED Lights

Illuminate control panel for night-time operation.

#### 32-Amp Socket Outlet

Run a food truck or other big unit load unit up to 6 kW.

#### Super Quiet

Low noise level ideal for home or public area use.

#### Mains Quality Electricity

Safe to power sensitive electronic equipment.

#### Electric Start

One touch power-up from the onboard 12-Volt battery.

#### Off-Grid Solar or Mains Backup

2-wire remote auto start, run and stop control.

#### Battery Charger

Keep your generator ready to go at all times.

#### 32 to 15-Amp Adaptor

Connect a standard plug into the 32-Amp socket.

#### Long Running

Up to 14.6 hours at 1/4 load with a 15 litre fuel tank.

#### Warranty Protection

2-year domestic use (conditions apply).



### Control Panel Functions

Run Time to Empty (hours) → Output Power (kW) → Fuel Level (litres) → Output Voltage (Volts) → Cumulative Run Time (hours)

10:29 → P2.88 → 06.0L → U240 → 0168



Powering People Since 1886.

# iGen7500As Inverter Generator

## Specifications

ENGINE		240 VOLT AC ELECTRICAL	
Type	1-Cylinder, 4-Stroke, Overhead Valve, Air Cooled	Voltage (V)	240
Displacement (cc)	298	Frequency (Hz)	50
Maximum Speed (rpm)	4,000	Number of Phases	1
Oil Capacity (mL)	650	Continuous Running Power (W) *	6,000
Oil Viscosity	SAE 10W-30	Maximum Starting Power (W)	7,500
Low Oil Shutdown	Yes	Continuous Running Current (A)	25
Low Oil Alarm Indicator	Yes	Voltage & Waveform Control	Digital Inverter, Pure Sine Wave Output
Spark Plug	Torch F7RTC	Total Harmonic Distortion (THD)	< 2.5%
Fuel	Unleaded Petrol # (91, 95 or 98 RON)	Receptacles	1 x 32 A, IP66 & 1 x 15 A, IP44
Fuel Tank Capacity (L)	15	Overload Protection	Electronic
Fuel Shutoff Valve	Yes, Independent	Overload Indicator	Yes
Starting Method	Local / Remote Electric and Recoil	Overload Reset	Push Button
Battery	12 V, Maintenance Free	Alternator	Brushless, Permanent Magnet
Run Time @ 1/4 / Full Load	14.6 / 4.6 hours	Output Ready Indicator	Yes
Noise Level @ 1/4 / Full Load	57 / 67 dB(A) @ 7 m TBA	Data Center Display	Output Power & Voltage, Fuel Level, Fuel & Cumulative Run Times
<b>DIMENSIONS &amp; WEIGHTS</b>		Control Panel Lights	LED, Operable At All Times
Generator L x W x H (mm)	690 x 530 x 550	<b>PRODUCT CODES</b>	
Generator Weight - Dry / Wet (kg)	60 / 73	Product Code	WP iGen7500AS
Packed L x W x H (mm)	857 x 580 x 593	GTIN Barcode	9347923003178
Packed Weight (kg)	70	# Ethanol blends such as E10 are not recommended. * Rated output at 1.0 power factor.	



Plug-In Battery Charger



Extendable Handle



Included Accessories