



Westinghouse

Consumer Guide

Inverter Generator Comparison



**Westinghouse
iGen2250**

**Westinghouse
2400i**

**Honda
EU22i**

**Yamaha
EF2000iS**

Engine Displacement	80 cc	79 cc	121 cc	79 cc
ECO Throttle Control	Yes	Yes	Yes	Yes
Low Oil Shutdown	Yes	Yes	Yes	Yes
Rated Electrical Output	1,800 Watts	2,100 Watts	1,800 Watts	1,600 Watts
Maximum Electrical Output	2,250 Watts	2,400 Watts	2,200 Watts	2,000 Watts
Rated AC Electrical Voltage	240 Volts	240 Volts	240 Volts	230 Volts
240 Volt AC Socket Outlets	2	2	2	1
240 Volt AC Overload Reset	Push Button	Push Button	Engine Restart	Engine Restart
12 Volt DC Cig. Lighter Socket	Yes	Yes	No	No
Digital Multifunction Display	Yes	Yes	No	No
Control Panel Lights	Yes	No	No	No
Single-Sided Control Access	No	Yes	No	Yes
Dimensions L x W x H	49 x 30 x 46 cm	50 x 34 x 44 cm	51 x 29 x 43 cm	49 x 28 x 45 cm
Weight (Dry)	19 kg	20 kg	21 kg	20 kg
Fuel Tank Capacity	4.7 Litres	5 Litres	3.6 Litres	4.4 Litres
Fuel Level Gauge	No	Yes	No	Yes
Fuel Shutoff Valve	Yes	Yes	Yes	Yes
Run Time @ 1/4 / Full Load	11.3 / 3.8 Hours	15.5 / 4.4 Hours	7.5 / 3.2 Hours	10.5 / 4.2 Hours
Noise Level @ 1/4 / Full Load (7 m)	53 / 62 dB(A)	53 / 62 dB(A)	Not Stated	51.5 / 61 dB(A)
Warranty (Domestic Use) *	2 Years	2 Years	4 Years ^Δ	4 Years
Warranty (Commercial Use) *	1 Year	1 Year	1 Year	1 Year
Recommended Retail Price	\$1,299	\$1,599	\$2,349	\$2,349

* Conditions apply.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised dealer.

Source: Manufacturers' websites as at 18 December 2024.

2025-01-10

Powering People Since 1886.