



Westinghouse

Consumer Guide

Inverter Generator Comparison



**Westinghouse
iGen3750s**

**Honda
EU32i**

**Yamaha
EF3000iSE**

Engine Displacement	141 cc	130 cc	171 cc
Engine Starter	Electric & Recoil	Recoil	Electric & Recoil
240 V AC Plug-In Battery Charger	Yes	No	No
Wireless Remote Control	Yes	No	No
Rated Electrical Output	3,000 Watts	2,600 Watts	2,800 Watts
Maximum Electrical Output	3,750 Watts	3,200 Watts	3,000 Watts
Rated AC Electrical Voltage	240 Volts	240 Volts	230 Volts
240 Volt AC Socket Outlets	2	2	2
240 Volt AC Overload Reset	Push Button	Push Button	Engine Restart
12 Volt DC Cig. Lighter Socket	Yes	No	No
Digital Multifunction Display	Yes	No	No
Control Panel Lights	Yes	No	No
Wheels	Yes	No	Yes
Dimensions L x W x H	55 x 32 x 49 cm	57 x 31 x 45 cm	68 x 45 x 56 cm
Weight (Dry)	27 kg	26.5 kg	67 kg
Fuel Tank Capacity	6.3 Litres	4.7 Litres	13 Litres
Fuel Level Gauge	No	Yes	Yes
Fuel Shutoff Valve	Yes	Not User Selectable	Yes
Run Time @ 1/4 / Full Load	8.8 / 3.0 Hours	8.5 / 3.3 Hours	20.5 / - Hours
Noise Level @ 1/4 / Full Load (7 m)	57 / 63 dB(A)	Not Stated	51 / 57 dB(A)
Warranty (Domestic / Commercial) *	2 / 1 Years	4 ^Δ / 1 Years	4 / 1 Years
Recommended Retail Price	\$2,299	\$4,199	\$4,785

* Conditions apply.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised dealer.

Source: Manufacturers' websites as at 18 December 2024.

2025-01-10

Powering People Since 1886.